



# PYC1125B

Prime Power:800KW/1000KVA Standby Power: 900KW/1125KVA Voltage: 400V

Powered by Yuchai YC6C1320-D31 Engine

## **Genset Performance**

- 230/400V, 50Hz, 0.8PF, 3 Phases 4 wires
- Frequency drop ≤3%
- Voltage regulation
- The steady state frequency <0.5%
- The steady state voltage deviation  $\leq \pm 1\%$
- The transient frequency deviation  $\leq$ +10%  $\leq$ -15%

≤3S

 $\leq$ 1S(Voltage $\pm$ 3%)

- The transient voltage deviation  $\leq$ +20%  $\leq$ -15%
- Frequency recovery time
- Voltage recovery time
- THF (Telephone Harmonic Factor) <3
- TIF (Telephone Influence Factor) <50</li>
  Comply to Standard NEMA MG1-22.43
- Standard equipped with ambient temperature 40°C
  Connecting radiator
- Built-in vibration isolator with high performance on shock absorption.
- Product standards: (1) GB/T 2820-2022 / IS08528:2018
  (2) GB/T 4712-2008 (3) YD/T 502-2020 (4)YD/T 1051-2018

## **Optional Items**

- Starting batteries
- Circuit breaker
- Fuel tank
- Oil-water separator
- Sensor for low coolant level, low fuel/oil level
- Automatically monitoring & controlling system of city power
- Coolant heater
- Oil heater
- Heat exchanger--Water cooled tower system
- Silent type/Trailer
- Standardized container
- Design and construction of environmental protection; engineering for the Genset room.

## **Standard Configuration**


- Guangxi Yuchai Engine
- Brushless synchronous alternator
- POWERTEC intelligent controller
- 40°C standard ambient temperature (50°C Optional)
- Float battery charger
- Battery connect wire
- Steel base frame
- Silencer, bellows, exhaust bend
- Manual book and files





## **Diesel Engine**

- Model: YC6C1320-D31
- The technologies of four valves and turbocharged & intercooled are adopted for ensuring sufficient air intake, full combustion and low fuel consumption.
- Electronic unit pump technology is adopted for ensuring stable operation, good transient speed governing performance, and strong loading capability;
- High-quality alloy cast iron cylinder block of reinforced grid structure with cambered surface, high-strength vermicular iron cylinder head, dual protection anti-impact cylinder gasket structure, and self-developed cooling technology for the bottom of the cylinder head are adopted, which ensure high reliability;



- The Yuchai proprietary carbon-scraping self-cleaning technology is adopted for ensuring low lubricating oil consumption;
- Electric pre-supply oil technology is adopted, which effectively protects kinematic pair and improves the service life of engine;
- The structure of one head for one cylinder is adopted; maintenance window is set at the side of the engine body, which ensures easy maintenance;
- YC6C1320-D31 series engine is a self-developed product by Yuchai combining the advanced technology for large engines both at home and abroad. The configurations, such as four valves, turbocharged & intercooled, and electronic unit pump, are adopted for it; and it is optimized and verified through the advanced combustion development technology of Yuchai, and is characterized by energy-saving and environment-friendly, high reliability, strong loading capability and good maintainability.

### Alternator

- Optional brands: Stamford / Marathon / Faraday / Engga / Mecc Alt
- Brushless, 4 pole rotating magnetic field, single bearing with protective cover.
- Insulation: H Class.
- IP Class: IP23
- Cooling system
- AC exciter, rotate rectifying
- The stator winding is impregnated and the surface is covered with moisture-proof epoxy insulating paint.
- Rotor and exciter made with high temperature insulating resin, to satify tough environment.
- Rotor dynamic balancing complys for BS5625, class 2.5
- Sealed with advanced lubricating grease to prolong life of bearing.





## **Standard Meters**

- 3 phases voltage: Ua, Ub, Uc
- Frequency F1
- Apparent power PR
- Power factor PF
- Coolant temperature WT
- Temperature °C display
- Oil pressure OP
- Engine speed

- 3 phases current: La, Lb, Lc
- Active power PA
- Power factor PF
- Temperature °C display
- KPa/Psi/Bar display
- Battery voltage V
- Running Hour
- Starting timer:(999999)



### **Standard Protection Function**

#### **Genset Protection**

Programmable I/O signal

#### **Engine Protection**

- Stop for over speed
- Low oil pressure
- High Coolant temperature
- Sensor fail

#### **Alternator Protection**

- Over Voltage
- Over current
- Voltage signal lost

#### **Control System Components**

- Manual/auto/stop/start
- Setting button
- Fault status indicators

- Emergency stop
- Alarm for low/high battery voltage
- Low battery voltage
- Fail to start/Cranking fail
- Over Voltage
- Over frequency
- Under frequency
- Screen menu selection button
- Emergency stop button
- Digital displayer



## **Communication Interface**

### (Option)

International standard MODBUS communication protocol RS232/RS485 is suitable for remote control and monitor; It is easy integrated with SCADA;.


## **Data sheet of Genset**



Genset				
Model	PYC1125B			
Prime Rating (kw)	800			
Standby Rating (kw)	900			
Rate current(A)	1443			
Power factor	0.8			
Frequency(Hz)	50			
Eng	ine			
Engine Model	YC6C1320-D31			
Gross Engine output-Prime (kw)	880			
Gross Engine output-Standby (kw)	968			
Bore * stroke (mm)	200*210			
Cylinders and structure	6 In line			
Displacement(Liter)	39.584			
Compression Ratio	14.5:1			
Intake way	Supercharge/Air-Air intercooling			
Max intake resistance (KPa)	6			
Air intake (m3/h)	4644			
Max exhaust back pressure (KPa)	10			
Exhaust gas flow (m3/h)	11352			
Exhaust temp (℃)	550			
Cooling way	Water Radiator & Fan			
Fan exhaust flow (m3/min)	1700			
Coolant capacity (L)	230			
Highest water temperature(°C)	97			
Minimum air opening to room (m2)	5.7/4.7			
Thermostat range (℃)	75-85			
Max oil temperature (°C)	120			
Lubrication system oil capacity (L)	160			
Rate load fuel consumption(L/H)	220.2			
Standard Governor/Class	Electronic unit pump			
Emission	China Tier 3			
Alterr	nator			
Rated Voltage(V)	230/400			
Output Way	3 Phases, 4 wires			
Rated power factor	0.8			
Exciter	Brushless, Self-exciter			
Max voltage regulation	±1%			
Phase	3			
Protection class	IP21-23			
Insulation class	Н			
Controller				
Brand	POWERTEC			

# **Dimension and Weight**






Silent Type

	— L ———		⊣₩
Туре	Dimension (mm) (L*W*H)	Weight (kg)	Fuel Tank Capacity (L)
Open Type	5007*1760*2544	8000	_

12200



1500

0

Co	onta	<b>a</b> t	
			US

0

## Powertec Generator System Inc.

6058\*2438\*2896

Add:	Danshui Yanna Industry Zone, Huiyang, Huizhou, Guangdong, China
Tel:	+86 752-3911119 / 3911118
Fax:	+86 752-3911110
Web:	www.powertec.com.cn
Email:	powertec@powertec.com.cn